

## B.02 Canonical forms of the state model

There are several canonical forms for the state equations, all of which can be found via basis transformations from other forms.

Phase-variable canonical form

The phase-variable canonical form is represented by the SISO<sup>1</sup> state model

$$\dot{x}_c = A_c x_c + B_c u \quad (1a)$$

$$y = C_c x_c + D_c u \quad (1b)$$

where

$$A_c = \begin{bmatrix} 0 & 1 & 0 & \dots & 0 & 0 \\ 0 & 0 & 1 & \dots & 0 & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & 0 & 0 & \dots & 1 & 0 \\ 0 & 0 & 0 & \dots & 0 & 1 \\ -a_0 & -a_1 & -a_2 & \dots & -a_{n-2} & -a_{n-1} \end{bmatrix}, \quad B_c = \begin{bmatrix} 0 \\ 0 \\ \vdots \\ 0 \\ 0 \\ 1 \end{bmatrix}, \quad (1c)$$

$$C_c = [c_1 \ c_2 \ \dots \ c_n], \text{ and} \quad (1d)$$

<sup>1</sup> There are phase-variable canonical forms for MIMO systems as well, but these are less standardized.

$$eig(A) = \lambda_1, \lambda_2, \dots$$

$$(s - \lambda_1)(s - \lambda_2) \dots$$

Eigen values  $\rightarrow$  characteristic polynomial

A in phase variable form

B in phase variable form

calculate v and u\_c

calculate T\_c

find A\_c B\_c C\_c and D\_c

In order to transform a SISO system (A, B, C, D) with state vector x to phase-variable canonical form, we change bases via the substitution of  $x = T_c x_c$  into the original system, which gives

$$A_c = T_c^{-1} A T_c, \quad B_c = T_c^{-1} B, \quad (2a)$$

$$C_c = C T_c, \text{ and} \quad D_c = D. \quad (2b)$$

The special form of Equation 1 yields the following characteristic polynomial:

$$s^n + a_{n-1}s^{n-1} + \dots + a_1s + a_0. \quad (3)$$

Recall that eigenvalues of a system are invariant to basis change, and therefore so is its characteristic polynomial. From this we can conclude that  $A_c$  can be completely determined by finding the characteristic polynomial of the original matrix A.  $B_c$  is already fully determined, but  $C_c$  and  $D_c$  remain undetermined. They may be found by discovering the transformation matrix  $T_c$  and substituting it into Equation 2.

Finding the phase-variable canonical transformation

The phase-variable canonical transformation matrix  $T_c$  can be found by relating the controllability matrices of the original form and the canonical form.

**Theorem B.4: phase-variable canonical transformation**

The transformation matrix from a system representation with controllability matrix  $U$  to a phase-variable canonical transformation with controllability matrix  $U_c$  is

$$T_c = U_c U^{-1}. \quad (4)$$

By the Definition of the controllability matrix, the original controllability matrix is

$$U = [B \ | \ AB \ | \ A^2B \ | \ \dots \ | \ A^{n-1}B] \quad (5)$$

and that of the canonical form is

$$U_c = [B_c \ | \ A_c B_c \ | \ A_c^2 B_c \ | \ \dots \ | \ A_c^{n-1} B_c]. \quad (6)$$

Note that  $U$  and  $U_c$  are both known from above. We relate the two forms by applying Equation 2 to Equation 6 to yield

$$U_c = [T_c^{-1} B \ | \ T_c^{-1} A B \ | \ T_c^{-1} A^2 B \ | \ \dots \ | \ T_c^{-1} A^{n-1} B] \quad (7a)$$

$$= T_c U, \quad (7b)$$

to yield

$$T_c = U_c U^{-1}.$$

C

Physical topics